Yuasa Scheda Tecnica

Yuasa NP17-12I Industrial VRLA Battery

Specifiche tecniche	
Tensione Nominale (V)	12
20-hr rate capacity to 1.75v per cell at 20°C (Ah)	17
10-hr rate Capacity to 1.75v per cell at 20°C (Ah)	15.7
Dimensioni	
Lunghezza (mm)	181 (±1)
Profondità (mm)	76 (±1)
Altezza (mm)	167 (±2)
Peso (kg)	6.1
Tipologia dei terminali	
Terminale filettato - (M = maschio o F femmina)	M5 (F)
Coppia di serraggio (Nm)	2.45
Range di temperatura d'esercizio	
Stoccaggio (con batteria carica al 100%)	-20°C to +60°C
Carica	-15°C to +50°C
Scarica	-20°C to +60°C
Stoccaggio	
Perdita di capacità per mese a 20°C (% approx.)	3
Materiale del contenitore	
Standard	ABS (UL94:HB)
Versione disponibile in FR	UL94:V0
Tensione di carica	
Carica a tampone a 20°C (V/batt)	13.65 (±1%)
Carica tampone a 20°C (V/el)	2.275 (±1%)
Coefficiente di correzione carica di tampone per temperature diverse da std 20°C (mV/°C/el)	-3
Tensione di carica ciclica o a fondo a 20°C V/batt	14.5 (±3%)
Tensione di carica ciclica o a fondo a 20°C V/el	2.42 (±3%)
Coefficiente di correzione carica ciclica con temperature diverse da std 20°C (mV/°C/el)	-4
Corrente di carica	
Limite di corrente di carica tampone (A)	No limit
Limite di corrente di carica ciclica o a fondo (A)	4.25
Corrente massima di scarica	
per 1 secondo (A)	500
per 1 minuto (A)	150
Corrente di corto circuito & resistenza interna	
Resistenza interna secondo IEC 60896-21 (mΩ)	34.47
Corrente di corto circuito secondo IEC 60896-21 (A)	421
Impedenza	
Misurata ad 1 kHz (mΩ)	15
Vita progetto ed approvazioni	
Classificazione Eurobat Standard Commercial\"	3 to 5 years
Yuasa design life a 20°C (anni)	up to 5



Layout



Certificazione di terze parti
ISO9001 - Sistema di gestione Qualità

Cert. No.: FM 10626

Sicurezza

Installazione
Può essere installata in ogni posizione eccetto permanentemente capovolta.

Maniglie
La batteria non può essere tenuta appesa dalle maniglie (dove presenti)

Valvole di ventilazione
Ogni singola cella è provvista di valvole a bassa pressione in grado di rilasciare gas in eccesso e richiudersi automaticamente.

Rilascio di gas
Le batterie VRLA possono rilasciare idrogeno, che può generare miscela esplosiva con l'aria. Non installare in contenitori ermetici.

Riciclo
Le batterie Yuasa devono essere riciclate a fine vita in accordo con le legislazioni e regolamentazioni locali.

Scheda tecnica prodotta su E&OE

Yuasa Technical Data Sheet

Yuasa NP17-12I Industrial VRLA Battery

Specifications	
Nominal voltage (V)	12
20-hr rate capacity to 1.75v per cell at 20°C (Ah)	17
10-hr rate Capacity to 1.75v per cell at 20°C (Ah)	15.7
Dimensions	
Length (mm)	181 (±1)
Width (mm)	76 (±1)
Height (mm)	167 (±2)
Mass (kg)	6.1
Terminal Type	
Threaded terminal - (M=Male or F=Female)	M5 (F)
Torque (Nm)	2.45
Operating Temperature Range	
Storage (in fully charged condition)	-20°C to +60°C
Charge	-15°C to +50°C
Discharge	-20°C to +60°C
Storage	
Capacity loss per month at 20°C (% approx.)	3
Case Material	
Standard	ABS (UL94:HB)
FR version available	UL94:V0
Charge Voltage	
Float charge voltage at 20°C (V)/Block	13.65 (±1%)
Float charge voltage at 20°C (V)/Cell	2.275 (±1%)
Float Chg voltage tmp correction factor from std 20°C (mV)	-3
Cyclic (or Boost) charge Voltage at 20°C (V)/Block	14.5 (±3%)
Cyclic (or Boost) charge Voltage at 20°C (V)/Cell	2.42 (±3%)
Cyclic Chg voltage tmp correction factor from std 20°C (mV)	-4
Charge Current	
Float charge current limit (A)	No limit
Cyclic (or Boost) charge current limit (A)	4.25
Maximum Discharge Current	
1 second (A)	500
1 minute (A)	150
Short-Circuit Current & Internal Resistance	
Internal resistance - according to EN IEC 60896-21 (mΩ)	34.47
Short-Circuit current - according to EN IEC 60896-21 (A)	421
Impedance	
Measured at 1 kHz (mΩ)	15
Design Life & Approvals	
EUROBAT Classification: Standard Commercial	3 to 5 years
Yuasa design life at 20°C (yrs)	up to 5



Layout



3rd Party Certifications
ISO9001 - Quality Management Systems

Safety

Installation
Can be installed and operated in any orientation except permanently inverted.

Handles
Batteries must not be suspended by their handles (where fitted).

Vent valves
Each cell is fitted with a low pressure release valve to allow gasses to escape and then reseal.

Gas release
VRLA batteries release hydrogen gas which can form explosive mixtures in the air. Do not place inside a sealed container.

Recycling
YUASA's VRLA batteries must be recycled at the end of life in accordance with local and national laws and regulations.

Data Sheet generated on 24/03/2023 – E&OE